



Features:

TH5201B AC withstand voltage insulation resistance tester

High-brightness VFD display, eye-catching, beautiful

0-5kVAC / DC voltage output AC current 100mA test

Insulation resistance test voltage is 100V / 500V / 1000V third gear, insulation resistance test test range:
200 k-1.0 G (100V)

Measure to protect ground open detection function

Analog, digital voltage indication

Upper and lower limits of the window comparator, PASS / FAIL judgment output

Single high voltage output of the AC / DC switch without changing the output terminals

Timed test function, zero start and zero-crossing off

Four special test mode selection, increase security testing

DC auto discharge function (TH5201)

Quality noise suppression circuit, improving the reliability of operation

REMOTE Security, signal input / output interface, RS-232C, user-friendly test operation, increased testing.

Model	TH5201B		
Hipot test			
Output voltage	AC	Voltage range	0-2.5kV / 0-5kV(Digital display 5%, Analog meter 5% F.S ..)
		Maximum output power	500 VA
		Voltage distortion	5%
		Voltage waveform	Power supply voltage waveform
	DC	HV ON/OFF	Zero start switch control
Current test range	AC	Voltage range	100V / 500V / 1000V (Digital display 5%, Analog meter 5% F.S ..)
		Maximum range power	1W (1.0kv, 1.0mA)
Resistance test range	AC	0 ~ 100mA	
		Accuracy of current	5% off the current limit
Resistance test range	Test range	100V: 200 kΩ-1.0 GΩ	
		500V: 1 MΩ-5.0 GΩ	
	Accuracy	1000V: 2 MΩ-10 GΩ	
General parameters			
Test time setting range	Timer ON: 0.2s-999s, the minimum resolution 0.1s		
Testing time accuracy	20ms		
Parameter save	Setting parameters are automatically saved (need at least after one measurement), the next boot automatically restore.		
Size	320 * 140 * 300 mm		
Weight	16 kg		
Interface			
REMOTE Control (Front Panel)	START, STOP, START-ENABLE, HV ON indication		
Signal input / output interface	Status output: PASS, U-FAIL, L-FAIL, PROTECTION, READY, TEST, HV-ON control: START, STOP, ENABLE, INTERLOCK special test mode setting: double effect, by keeping the instant test, not by keeping.		
Communication Interface	RS232C		